



Printed Pages : 4

TEE501

(Following Paper ID and Roll No. to be filled in your Answer Book)

PAPER ID : 2055

Roll No.

--	--	--	--	--	--	--	--	--	--

B.Tech**(SEM V) ODD SEMESTER THEORY EXAMINATION 2009-10
ELECTROMECHANICAL ENERGY CONVERSION- II**

Time : 3 Hours]

[Total Marks : 100

Note : Attempt all questions.**1** Attempt any **four** of the following : **5×4=20**

- (a) Draw and explain the equivalent circuit diagram and phasor diagram of a synchronous machine.
- (b) What is armature reaction ? What measures are taken to overcome its effect and how ?
- (c) What do you know about voltage regulation of an alternator ? Name the various methods of obtaining the same. Describe any one of them in detail.
- (d) How does the parallel operation of two alternators differ from the condition when an alternator runs with an infinite bus bar ? How is the power sharing affected in parallel operation when (i) Excitation of one of them is changed and (ii) Steam input to one of them is changed ?
- (e) Discuss about synchronizing power.



- (f) Explain power angle characteristics of cylindrical rotor alternator.

2 Attempt any **two** of the following : **10×2=20**

- (a) What is the effect of saliency of field poles in the synchronous machines ? Draw a phasor diagram showing relationship between the induced emf and the terminal voltage for an alternator running over excited.
- (b) The full load current of a 3.3 kV, star connected synchronous motor is 160 A at 0.8 p.f. lagging. The resistance and synchronous reactance of the motor are **0.8Ω** and **5.5Ω** per phase respectively. Calculate the excitation emf, torque angle, efficiency and shaft output of the motor. Assume the mechanical stray load loss to be 30 kW.
- (c) Discuss about the following :
- (i) Hunting
 - (ii) Damper winding
 - (iii) V-curves.

3 Attempt any **four** of the following : **5×4=20**

- (a) Describe the principle of rotating magnetic field in a 3 phase induction motor.
- (b) Draw the slip-torque characteristics of 3 ph. induction motors at subsynchronous, supersynchronous and reverse direction speeds. Explain the physical meaning of these modes of operation.

- (c) Develop an equivalent circuit diagram for a three phase induction motor. Show in the circuit that $R_2 \left(\frac{1-s}{s} \right)$ is the electrical equivalent of mechanical load on motor, where R_2 is the rotor resistance.

- (d) A 6-pole, 50 Hz, 3 phase induction motor running on full load develops a useful torque of 160 Nm when the rotor emf makes 120 complete cycles per minute. Calculate the shaft power output.
- (e) Derive the expression for torque in a 3 phase induction motor. How is this affected by the rotor parameters ? Draw suitable slip torque characteristics to show the variation in torque due to change in rotor resistance.
- (f) A 4-pole, 400 V, 3 phase induction motor has a stand still reactance of 0.5 ohm per phase, standstill rotor emf of 100 V per phase and rotor resistance of 50 milli ohm per phase. Calculate the maximum torque and the slip at which it occurs. Neglect the stator impedance.

4 Attempt any **two** of the following : **10×2=20**

- (a) Why starter is needed for operation of 3-phase induction motor ? List different starting methods of slip ring type and squirrel cage type induction motors. An induction motor has a starting current of six times the full load current and a full load slip of 0.05. Find in PU of full-load values the line current and starting torque with
- (i) Direct starting
 - (ii) Star-delta starting.

(b) Explain the role of deep bar and double cage rotor in squirrel cage induction motor. The impedances at standstill of the inner and outer cages of a double cage rotor are $(0.01 + j0.5)\Omega$ and $(0.05 + j0.1)\Omega$ respectively. The stator impedance may be assumed negligible. Calculate the ratio of the torques due to the two cages :

(i) at starting

(ii) when running with a slip of 5%

(c) Explain constant (U/f) method of speed control of 3 phase induction motor. A 50 Hz, 3-phase induction motor has a rated voltage V_1 . The motor's break down torque at rated voltage and frequency occurs at slip of 0.2. The motor is run from a 60 Hz supply of voltage V_2 . The stator impedance can be neglected.

Find the ratio of currents and torques at starting if

$$V_2 = V_1.$$

5 Attempt any **two** of the following : 10×2=20

- (a) Why is a 1-phase induction motor non-self starting ? Explain double revolving field theory in detail.
- (b) Explain about single phase ac series compensated motor in detail.
- (c) What do you know about stepper motors ? What are the areas of application of the same ?

