

Printed Pages:

Paper Id:

2	2	0	2	2	2
---	---	---	---	---	---

Sub Code: PEE-22

Roll No.

--	--	--	--	--	--	--	--	--	--

**M.TECH
(SEM-II) THEORY EXAMINATION 2017-18
ADVANCED CONTROL SYSTEM**

Time: 3 Hours

Total Marks: 100

- Note:** 1. Attempt all Sections. If require any missing data; then choose suitably.
2. Any special paper specific instruction.

SECTION A

1. Attempt *all* questions in brief. 2 x 10 = 20

- a. What are the advantages of state space analysis?
- b. What are the properties of state transition matrix?
- c. What are linear system and non linear system give example?
- d. Explain sufficient conditions for stability?
- e. Discuss the concept of formulation of the optimal control problem?
- f. What is intelligent control?
- g. What is need for observability test?
- h. Define controllability?
- i. Define asymptotic stability?
- j. What is singular point?

SECTION B

2. Attempt any *three* of the following: 10 x 3 = 30

- a. Derive the expression for n^{th} order system characteristic polynomial when conversion takes place from state variable model to transfer function model.
- b. A system characterized by following state space equation:

$$A = \begin{bmatrix} -3 & 1 & 1 \\ -1 & 0 & 1 \\ 0 & 0 & 1 \end{bmatrix}, B = \begin{bmatrix} 0 & 1 \\ 0 & 0 \\ 2 & 1 \end{bmatrix}, C = \begin{bmatrix} 0 & 0 & 1 \\ 1 & 1 & 0 \end{bmatrix}$$

Investigate its controllability and observability.

- c. Find the Lyapunov function for the following system:

$$\begin{bmatrix} \dot{x}_1 \\ \dot{x}_2 \end{bmatrix} = \begin{bmatrix} -1 & 1 \\ 2 & -4 \end{bmatrix} \begin{bmatrix} x_1 \\ x_2 \end{bmatrix}$$

- d. Discuss linearization of non-linear system.
- e. Write short notes on: (i) deadzone non linearity (ii) saturation non linearity

SECTION C

3. Attempt any *one* part of the following: 10 x 1 = 10

- (a) Write the statement of sampling theorem. Draw the block diagram representation of S/H device.
- (b) Using Liapunov method investigate the stability of the following system

$$\begin{bmatrix} \dot{x}_1 \\ \dot{x}_2 \end{bmatrix} = \begin{bmatrix} 0 & 1 \\ -1 & -1 \end{bmatrix} \begin{bmatrix} x_1 \\ x_2 \end{bmatrix}$$

- 4. Attempt any *one* part of the following: **10 x 1 = 10****
- (a) Define optimal control for performance index. Write the performance indices of minimum time, minimum fuel, and minimum energy.
 - (b) Discuss relationship between Z-domain and S-domain.
- 5. Attempt any *one* part of the following: **10 x 1 = 10****
- (a) Explain the concept of stability in Z- plane.
 - (b) Discuss (i) limit cycle (ii) jump resonance
- 6. Attempt any *one* part of the following: **10 x 1 = 10****
- (a) Derive the Gilbert's test for checking observability and controllability of the system
 - (b) What is adaptive control? What are the schemes in adaptive control? Discuss in brief.
- 7. Attempt any *one* part of the following: **10 x 1 = 10****
- (a) Explain how to study the stability of the system through describing function analysis.
 - (b) Explain jury stability criterion. Consider characteristic polynomial:
 $F(Z) = 2Z^4 + 7Z^3 + 10Z^2 + 4z + 1$. Check stability of this system.