

Printed Pages—3

ECS603

(Following Paper ID and Roll No. to be filled in your Answer Book)

PAPER ID : 110603 Roll No. 

--	--	--	--	--	--	--	--	--	--

**B.Tech.**

(SEM. VI) THEORY EXAMINATION 2013-14

**COMPILER DESIGN***Time : 3 Hours**Total Marks : 100***Note :-** (1) Attempt all questions. Each question carries equal marks.

(2) Be precise and to the point while answering.

1. Attempt any four parts : (5×4=20)
  - (a) Describe the synthesis-analysis model of compiler.
  - (b) What are different compiler tools ? Discuss any two.
  - (c) Remove left recursion from the grammar  
 $E \rightarrow E(T) | T$   
 $T \rightarrow T(F) | F$   
 $F \rightarrow id$
  - (d) What do you mean by ambiguous grammar ? Show that the following grammar is ambiguous.  
 $S \rightarrow a S b S | b S a S | \epsilon$
  - (e) Define boot-strapping with the help of an example.
  - (f) Explain the term token, lexeme and Pattern.
2. Attempt any two parts : (10×2=20)
  - (a) What do you mean by operator precedence grammar ?

ECS603/DQJ-21752

1

*[Turn Over*

Compute the operator precedence table for the given grammar.

$$E \rightarrow E + T \mid T$$

$$T \rightarrow T * F \mid F$$

$$F \rightarrow (E) \mid id$$

- (b) Differentiate between Recursive Decent Parsing and Predictive Parsing. Derive the LL (1) parsing table for the following grammar

$$bexpr \rightarrow bexpr \text{ or } bterm \mid bterm$$

$$bterm \rightarrow bterm \text{ and } bfactor \mid bfactor$$

$$bfactor \rightarrow \text{not } bfactor \mid (bexpr) \mid \text{true} \mid \text{false}$$

- (c) Show that the following grammar

$$S \rightarrow Aa \mid bAc \mid Bc \mid bBa$$

$$A \rightarrow d$$

$$B \rightarrow d$$

is LR (1) but not LALR (1).

3. Attempt any two parts : (10×2=20)

- (a) Define Syntax Directed Translation. Construct an annotated parse tree for the expression  $(4 * 7 + 1) * 2$ , using the simple desk calculator grammar.

- (b) What are different ways to write three address code ? Write the three address code for the following code segment :

While  $A < C$  and  $B < D$  do

if  $A = 1$  then  $C = C + 1$

else while  $A \leq D$  do  $A = A + 2$ .

- (c) Define backpatching and semantic rules for boolean expression. Derive the three address code for the following expression

$P < Q$  and  $R < S$  and  $T < U$

4. Attempt any two parts : (10×2=20)

- (a) What is the role of symbol table ? Discuss different data structures used for symbol table.
- (b) What are lexical phase errors, syntactic phase errors and semantic phase errors ? Explain with suitable example.
- (c) Why run-time storage management is required ? How simple stack implementation is implemented ?

5. Attempt any two parts : (10×2=20)

- (a) What is DAG ? How DAG is created from three address code ? Write algorithm for it and explain it with a relevant example.
- (b) What are different issues in code optimization ? Explain it with proper example.
- (c) Write short notes (any two) :
- (i) Global Data Flow Analysis
  - (ii) Loop unrolling
  - (iii) Loop Jamming.