

Determine :—

- (i)  $H(z)$ , the system function,
- (ii)  $h(n)$ , the unit-sample response sequence and
- (iii) transfer function  $H(e^{j\omega})$ .

Also plot its magnitude response.

(b) Find the voltage transfer functions,  $H(S)$ , of the following :—

- (i) The L-section RC high pass filter.
  - (ii) The L-section LC low pass filter.
- (c) Obtain canonical direct form, cascade and parallel realizations of the transfer function :

$$H(s) = \frac{5s^3}{s^3 + 6s^2 + 11s + 6}$$

Printed Pages : 4

EEC404

(Following Paper ID and Roll No. to be filled in your Answer Book)

PAPER ID 1324

Roll No.

**B.Tech.**

(SEM. IV) THEORY EXAMINATION 2010-11

**SIGNALS AND SYSTEMS**

Time : 3 Hours

Total Marks : 100

Note :— (1) Attempt ALL questions. All questions carry equal marks.

(2) Be precise in your answer. No second answer book will be provided.

1. Attempt any **FOUR** parts of the following :—  $5 \times 4 = 20$

- (a) Define a continuous-time signal and show that the product of two odd signals is an even signal.
- (b) Determine and sketch the even and odd components of the continuous-time signal  $x(t) = e^{-t} u(t)$ .
- (c) Consider  $x(t) = \cos 2\pi f_c t$ . Is it a power signal or energy signal ?
- (d) Write down the expression for and plot the sinusoidal discrete-time sequence whose peak amplitude is 10 and frequency is 100 Hz. The sampling frequency is 1000 samples per second.
- (e) Define unit impulse function and also state at least three properties of it.
- (f) Show whether  $x(t) = \begin{cases} A; & 0 < t < T_0 \\ 0; & \text{otherwise} \end{cases}$  is an energy signal or power signal.

2. Attempt any **FOUR** parts of the following :—  $5 \times 4 = 20$

(a) State and prove the initial value theorem for a function  $f(t)$ .

(b) Using partial fraction expansion, find  $f(t)$ . If its unilateral Laplace Transform  $F(s)$  is given by

$$\frac{2s-1}{s^2+2s+1}$$

(c) Determine the energy contained in the signal

$$x(t) = 20 \sin 10t.$$

(d) Show that the Z-transform of any anti-symmetric sequence has a zero at  $z = 1$ .

(e) Find the unilateral Z-Transform of

$$x(n) = [a^n \cos \omega_0 n] u(n).$$

(f) If  $X(z) = \frac{z}{3z^2 - 4z + 1}$ , find  $x(n)$ ,  $n \geq 0$ , given that

$$\text{ROC of } X(z) \text{ is } |z| > 1.$$

3. Attempt any **FOUR** parts of the following :—  $5 \times 4 = 20$

(a) Determine and sketch spectrum of

$$x(t) = 10 \sin 2 \pi f_0 t.$$

(b) Show that the convolution in time domain is same as product in frequency domain.

(c) Find the Fourier transform of  $x(t) = \frac{1}{1+t^2}$ .

(d) Compute the DTFT of

$$x(n) = (a^n \cos \omega_0 n) u(n); a < 1.$$

(e) If  $X(e^{j\omega}) = 2 \pi \delta(\omega)$ ;  $-\pi < \omega < \pi$ . Find  $x(n)$ .

(f) State and prove the multiplication theorem for two discrete signals.

4. Attempt any **TWO** parts of the following :—  $10 \times 2 = 20$

(a) (i) A particular system has been modeled by an input-output relation

$$Y(t) = a_0 + a_1 x(t) + a_2 x^2(t)$$

(ii) Is the system static or dynamic ?

(iii) Is it linear ? Justify your answer.

(iv) Show that an ideal differentiator which input  $x(t)$  and output  $y(t)$  related by  $y(t) = \frac{dx(t)}{dt}$  is a linear time invariant system.

(b) For the DT system described by the difference equation

$$y(n) = 0.6y(n-1) - 0.08y(n-2) + x(n),$$

determine :

(i) The unit-sample response sequence,  $h(n)$ ,

(ii) The step-response sequence  $g(n)$  and

(iii) Whether it is BIBO stable ?

(c) (i) Find the auto-correlation function and the Energy Spectral Density (ESD) of the signal

$$x(t) = e^{-t} u(t).$$

(ii) Given  $x(t) = 5 \cos t$  and  $y(t) = 2e^{-t}$ , find convolution  $x(t) * y(t)$ .

5. Attempt any **TWO** parts of the following :—  $10 \times 2 = 20$

(a) A second-order DT system is described by the difference equation :

$$y(n) - y(n-1) + 0.5y(n-2) = x(n).$$