

(Following Paper ID and Roll No. to be filled in your Answer Book)

PAPER ID : 3039

Roll No.

--	--	--	--	--	--	--	--	--	--	--

B.Tech.

SIXTH SEMESTER EXAMINATION, 2004-2005

DIGITAL COMMUNICATION

Time : 3 Hours

Total Marks : 100

Note : (i) Answer *ALL* questions.

(ii) All questions carry equal marks.

(iii) In case of numerical problems assume data wherever not provided.

1. Attempt *any four* parts of the following : (5x4=20)

- (a) A DMS has an alphabet of 8 letters $x_i, i=1, \dots, 8$ with probabilities 0.25, 0.20, 0.15, 0.12, 0.10, 0.08, 0.05 and 0.05. Determine an optimum binary code for the source using Huffman Coding procedure.
- (b) Let X be output of a DMS with letters a_1, a_2, a_3 in its alphabet with probabilities 0.45, 0.35 and 0.20. X is transformed to Y by following linear operation $Y = aX + b$ where a and b are constants. Determine entropy of Y .
- (c) Prove that for a DMS an optimum code exists in which lower probability letters consistently have higher length codewords.
- (d) Show that $I(x; y) \leq \min. \{H(x), H(y)\}$.

- (e) What is Shannon limit ? Determine its value.
- (f) Find minimum bandwidth needed for transmission if 6 messages of 20 KHz bandwidth each are multiplexed using FDM followed by SSB modulation.

2. Attempt *any four* parts of the following : (5x4=20)

- (a) A sinusoidal signal is input to a mid tread type uniform quantizer. Draw the quantizer output for one cycle of the input.
- (b) Show that for a uniform quantizer with a given dynamic range, if the number of quantization levels is doubled then signal-to-quantization noise power increases by 6 dB.
- (c) What is the A-law of companding ? Give its expression and draw it.
- (d) What is the maximum power of a sinusoidal input to a delta modulator with step size D, if no slope-overload distortion is to take place. The sampling interval is T_s .
- (e) What is sigma-delta modulator ? Give its block-schematic diagram ?
- (f) What is T3 system ? Describe it briefly.

3. Attempt *any two* parts of the following : (10x2=20)


- (a) (i) Let $X_\alpha(f)$ be the raised cosine spectrum with roll-off factor α . Show that

$$\int_{-\infty}^{\infty} X_\alpha(f) df = 1.$$

- (ii) What is minimum bandwidth solution for pulse shape with zero ISI ? Assume symbol duration is T .
- (b) Given a bit sequence of 01011001, draw line codes in NRZ-L, NRZI and pseudoternary formats. Compare them on the basis of their bandwidth and clocking capability.
- (c) Derive the optimum correlation receiver structure for coherent reception in AWGN channel.

4. Attempt *any two* parts of the following : (10x2=20)


- (a) Derive the probability of bit error for QPSK scheme in AWGN channel.
- (b) Apply gram-schmidt procedure to following signals to obtain an orthonormal basis set and signal coordinates.



- (c) Digital information is to be transmitted by carrier modulation through an AWGN channel with a bandwidth of 100KHz and $N_0 = 10^{-10}$ W/Hz. Determine the maximum rate that can be transmitted through the channel for :
 - (i) Four phase PSK
 - (ii) Binary FSK
 - (iii) Four-frequency orthogonal FSK with incoherent reception.

5. Attempt *any two* parts of the following : (10x2=20)

- (a) Show that a block code with hamming distance of $2t + 1$ can detect at most $2t$ bit errors and correct upto t -bits of errors using minimum distance decoding rule.
- (b) (i) Show that a cyclic code with $(1 + x)$ as factor of its generator polynomial will detect all odd number of bit errors.
- (ii) Let $g(x) = x^8 + x^6 + x^4 + x^2 + 1$ be a polynomial over the binary field. Find the lowest rate cyclic code whose generator polynomial is $g(x)$.
- (c) Consider a convolutional coder with following structure.



- (i) Determine its rate, constraint length and generators.
- (ii) Determine its state diagram and transfer function.

** *** **