

Printed Pages: 02

Paper Id:

1	3	2	6	3	2
---	---	---	---	---	---

Sub Code: NEC602

Roll No.

--	--	--	--	--	--	--	--	--	--

B TECH
(SEM VI) THEORY EXAMINATION 2017-18
DIGITAL COMMUNICATION

Time: 3 Hours**Total Marks: 100**

- Note:** 1. Attempt all Sections. If require any missing data; then choose suitably.
2. Any special paper specific instruction.

SECTION A

1. **Attempt all questions in brief.** **2 x10 = 20**
- What is base band and pass band signaling?
 - Define linear time invariant system?
 - Differentiate between wide sense stationary and strict sense stationary random process?
 - For error free communication over a channel how channel capacity and entropies are being related?
 - Compare the probability of error for ASK and BPSK modulation technique?
 - Define the term processing gain?
 - Sketch 1110010 waveform by using Manchester and NRZ(L) line coding scheme?
 - What is slow and fast frequency hopping technique?
 - How source coding is different to that of channel coding?
 - What is AWGN channel?

SECTION B

2. **Attempt any three of the following:** **10 x 3 = 30**
- What is differential encoding? With suitable diagram explain DPSK modulator and demodulator?
 - What is ISI? Explain how ISI can be removed by employing a raised cosine filter?
 - Write down the characteristics and necessity of source coding in communication system? Consider a source with 03 messages having symbol probabilities 0.5, 0.4, 0.1. Obtain Shannon Fano code and calculate its coding efficiency?
 - Differentiate between random variable and random process? A random variable has an exponential probability density function given by $f(x) = ae^{-b|x|}$ where a and b are constant. Find the relationship between a and b?
 - A rate 1/3 convolutional encoder has generator matrix $g_1=100, g_2=111, g_3=101$
 - Sketch the encoder
 - Draw the code tree and trellis
 - If input is 10110 determine the output?
 - What is coherent and non-coherent reception technique? With a suitable detailed block diagram explain coherent digital receiver?

SECTION C

3. **Attempt any one part of the following:** **10 x 1 = 10**
- With suitable diagram describe matched filter? Prove that output signal of a matched filter is proportional to a shifted version of the autocorrelation function of the input signal to which filter is matched?
 - What is the relevance of M-ary signaling? Explain M-ary PSK modulation

technique and draw its constellation diagram?

4. Attempt any one part of the following: 10 x 1 = 10

- (a) Write short note on
- Gaussian random variable
 - Power spectral density for wide sense stationary random process
- (b) Explain how spread using CDMA technique can use spectrum communication for providing multipoint connectivity?

5. Attempt any one part of the following: 10 x 1 = 10


- (a) What is mutual information and how it is related to channel capacity. For a standard voice band communication channel the signal to noise ratio is 30dB and transmission bandwidth is 3KHz. What will be the Shannon limit for information in bits/sec?
- (b) An information source produces 8 different symbols with probability $1/2, 1/4, 1/8, 1/16, 1/32, 1/64, 1/128, 1/256$ respectively. These symbols are encoded as 000,001,010,011,100,110 and 111 respectively.
- What is the amount of information per symbol?
 - What is the probability of occurrence for 0 and 1?
 - What is the efficiency of the obtained code?

6. Attempt any one part of the following: 10 x 1 = 10

- (a) Define the entropy? Prove the relationship between different entropies
 $H(XY) = H(Y/X) + H(X)$
- (b) Design a block code with a minimum distance of three and a message block of eight bits?

7. Attempt any one part of the following: 10 x 1 = 10

- (a) What is Minimum Shift Keying Modulation (MSK) technique? Write down the difference between QPSK and MSK?
- (b) A P-N sequence is generated by using a feedback shift register of length four. Find the generated output sequence if the initial contents of the shift register are 1000. If the chip rate is 10^7 chip/sec. Calculate the chip and P-N sequence duration and period of output sequence?



clock

12.05.18 EVENING
KINDLY READ QUESTION AS BELOW

Q5.

- (b) An information source produces 8 different symbols with probability $1/2, 1/4, 1/8, 1/16, 1/32, 1/64, 1/128, 1/256$ respectively. These symbols are encoded as 000,001,010,011,100,101, 110 and 111 respectively.
- i. What is the amount of information per symbol?
 - ii. What is the probability of occurrence for 0 and 1?
 - iii. What is the efficiency of the obtained code?