

Paper Id: **910051**

Roll No:

| | | | | | | | | | | |
|--|--|--|--|--|--|--|--|--|--|--|
| | | | | | | | | | | |
|--|--|--|--|--|--|--|--|--|--|--|

4. Attempt any two part of the following: 5 x 2 = 10


- (a) Explain half wave and quarter wave symmetry in Fourier series.
- (b) Explain convolution and multiplication property of Fourier transform.
- (c) Find the frequency response $H(\omega)$ and impulse response $h(t)$ of the LTI system.

$$d^2y(t)/dt^2 + 4dy(t)/dt + 3y(t) = dx(t)/dt + 2x(t)$$

5. Attempt any two part of the following: 5 x 2 = 10

- (a) Determine inverse Laplace transform of the function


$$s^2/(s-1)(s-0.5)^2$$
- (b) Consider the R-L circuit with $R = 4\Omega$ and $L = 1H$ excited by a 48V d.c. source as shown in figure. Assume the initial current through the inductor is 3A. Using the Laplace transform determine the current $i(t)$; $t \geq 0$. Also draw the s-domain representation of the circuit.



- (c) Find the Laplace transform of $1/(s^2+9s+20)$ For the signal $y(t) = t^2x(t)$

6. Attempt any two part of the following: 5 x 2 = 10

- (a) Find the transfer function for the system which is represented in state space representation as follows:



- (b) Find the state equation for the system shown in figure.

$$\begin{bmatrix} \dot{x}_1 \\ \dot{x}_2 \\ \dot{x}_3 \end{bmatrix} = \begin{bmatrix} -2 & 1 & 0 \\ 0 & -3 & 1 \\ -3 & -4 & -5 \end{bmatrix} \begin{bmatrix} x_1 \\ x_2 \\ x_3 \end{bmatrix} + \begin{bmatrix} 0 \\ 0 \\ 1 \end{bmatrix} u$$

$$y = [0 \quad 1 \quad 0] \begin{bmatrix} x_1 \\ x_2 \\ x_3 \end{bmatrix}$$

- (c) Draw and explain state models for linear time invariant systems.

7. Attempt any two part of the following: 5 x 2 = 10

- (a) Evaluate the inverse z transform of $X(z) = 1/(1-2z^{-1})$, $|z| > 2$ using the contour integration method.
- (b) Determine the z- transform of the following signal
 $g_1(n) = a^n \cos(\omega_0 n) u(n)$
- (c) Find $x(\omega)$ if $X(z)$ is given by

$$X(z) = \frac{z+1}{z(z-1)(z+0.5)}$$