

Printed Pages : 4



EEE-702/EEE-035

(Following Paper ID and Roll No. to be filled in your Answer Book)

PAPER ID : 120701/121756

Roll No.

--	--	--	--	--	--	--	--	--	--

**B. Tech.**

(SEM. VII) (ODD SEM.) THEORY  
EXAMINATION, 2014-15  
ELECTRIC DRIVES  
(ELECTRICAL ENGG.)

Time : 3 Hours]

[Total Marks : 100

- 1 Attempt any **four** parts of the following : **5×4=20**
- Draw the block diagram of an electric drive. Explain the function of Power modulator in detail.
  - State the advantages of drive system. Give some applications with suitable drive system.
  - Illustrate the Drive characteristics in detail with applications.
  - Explain the constant torque and constant power characteristics.
  - Elucidate the multi-quadrant operation of drive system.
  - Explain the components of motor-load dynamics.

120701-121756]

1

[ Contd...

2 Attempt any **two** parts of the following : **10×2=20**

- a) Discuss the dynamics of motor load system and also derive the relations for motor- load torque system.
- b) Combine the speed torque characteristics of various load and motor and comment on steady state stability of them.
- c) Write short notes on classes of Duty in detail with examples.

3 Attempt any **two** parts of the following : **10×2=20**

- a) A 230V, 500 rpm, 100A separately excited dc motor has an armature resistance  $0.1 \Omega$  is now coupled to an overhauling load with a torque of 800 N-m. Determine the speed at which the motor can hold the load by regenerative braking. Neglect the motor's rotational losses.
- b) Explain the various methods of braking can be applied to induction motor. And also state what kind of braking is more effective, justify it.

120701-121756]

2

[ Contd...

- c) Derive the expression to calculate the energy loss during starting of Induction motor and also State the various methods used to used to reduce the energy loss during starting.

4 Attempt any **two** parts of the following : **10×2=20**

- a) A 200 V, 875 rpm, 150 A separately excited dc motor has an armature resistance of 0.06 ohms. It is fed from a single phase fully controlled rectifier with an ac source voltage of 220V, 50HZ assuming continuous conduction.

Calculate

- i) Firing angle for rated motor torque and 750 rpm.
- ii) Firing angle for rated motor torque and (-500 rpm)
- b) Explain the operation of separately excited DC motor Drive which is excited by two converters simultaneously.

120701-121756]

3

[ Contd...

- c) A 230V, 100rpm, 20A dc separately excited motor has the armature resistance and inductance of  $1\ \Omega$  and 50mH, respectively. The motor is controlled in regenerative braking by a chopper operating at 600Hz.
- i) Calculate the motor speed and the regenerated power for  $\eta=0.5$  and the rated torque.
- ii) What is the maximum armature current ripple?

5 Attempt any **two** parts of the following :  $10 \times 2 = 20$

- a) Explain how the Static Scherbius drive is used in slip power recovery scheme.
- b) Describe in detail about speed control of self controlled synchronous motor drives.
- c) Elucidate the operation of Brushless dc motor drive in detail.

---

120701-121756]

4

11900